

turn voice into  action

## Digta CordEx

Wireless USB dictation microphone



### Digta CordEx

#### Enjoy full freedom of movement during dictation!

The Digta CordEx combines all the benefits of desktop dictation with the flexibility of a mobile dictation device. The user is no longer restricted to work at the desk because of a cable connection. The extra wide four-step slide switch with intuitive operation is extremely easy to use.

Especially important for this new style of dynamic dictating: Thanks to the high capacity rechargeable battery and an optional spare rechargeable battery the Digta CordEx allows almost unlimited dictating.

Overview of the Digta CordEx:

- Ergonomic design
- Color display with indication of status and menu control
- Internal memory buffer for voice data
- No permission for radio transmission necessary (also for use in medical areas)

Please check in advance for any legal restrictions regarding radio transmission in the designated area of application. GBS can not guarantee that a permission is not necessary.

- Versatile docking station which performs as a:
  - Base transceiver station
  - USB data interface to the PC
  - Charging station (for the device and the extra battery)
  - Foot control connection
- Including professional dictation software DigtaSoft One/DigtaSoft



Including docking station ...



... and can be combined with  
RFID reader / barcode reader

## Digta CordEx

### User controls



### Functions/Equipment

Connection to PC	USB connection
Sound card	Built-in sound card for optimum voice quality
Recording/ playback, stop, fast forward, rewind	4 function slide switch
Function buttons	3 operating buttons (Record, Insert, Info/Index) 3 function buttons – threefold programmable Windows control functions as required
LED	Recording red, insert: orange, info: blue
Display	OLED colour display for menu control and indication of current status (field strength, memory buffer, charging and operation mode-record, play-back, pause, stop)
Ergonomics	Ergonomic operation, stretched case design for comfortable dictation
File format	Application dependent (for ex. DSS or DSSPro with DigtaSoft)
Cable-bound emergency power supply	Adaptor to plug the microphone to the USB connector of the PC for power supply or to a mains unit
DigtaSoft One/DigtaSoft	PC software for the easy recording, transfer, processing and sending of dictations on DigtaSoft networks and configuration of dictation machine. Digta Soft One especially focuses on the basic recording and play-back functions for those wanting a quick start into the world of digital dictating.

### Technical data microphone

Display	Graphic display (OLED) 132 x 64 Pixel
PC interface	USB 1.1-Interface
USB connecting device	USB Audio Device, USB HID
Frequency response	200 Hz–7500 Hz ± 2 dB
Radio transmission	RF 2,4 GHz Transceiver, ISM-Band, GFSK-Modulation
Data rate	Max. 2 Mbit/s radio transmission
Transmitting power	Max. 1 mW
Radio range	A maximum of up to 26 ft (8 m)
Speaker	Dynamic speaker, diameter 1.1 inch (28 mm) Power output 300 mW
Power consumption	Max. 650 mW
Power supply	Li-Polymer 950 mA, 3,7 V rechargeable battery
Service life	Up to 8 hrs of voice recordings
Housing color	Sonic Black
Temperature for storage	-4°F to +122°F
Temperature for operation	+32°F to +104°F
Size	Length 8.35 inch (212 mm) x W1.57 inch (40 mm) x D0.79 inch (20 mm)
Weight	Microphone approx. 4.93 inch (140 g)
System requirements	Windows 2000 SP4 roll up 1 and higher/XP SP2/ Vista, USB 1.1 interface

### Indicator

### Technical data docking station

	Charging LED yellow; USB: green
PC interface	USB 1.1 interface, connector cable USB A/ Mini USB plug
Power supply	USB (self-powered – 500 mA) and mains/charger unit 475
Housing color	Sonic Black
Size	H5.35 inch (136 mm) x W1.81. inch (46 mm) x D5.43 inch (138 mm)
Weight	Approx. 290 g

### Scope of delivery

Digta CordEx, including rechargeable battery
Docking station, incl. USB connector cable and adaptor for wired power supply of the microphone, Power supply/charger unit 475
Digta Hardware CD with AdapterServer for configuring the buttons and functions

### DigtaSoft Pro

### Optional accessories

PC software with additional features like extended memory and export functions, comfort settings for player, a reporting tool and others. An upgrade from DigtaSoft is possible at any time.

Barcode reader	Digta Scan 404, color Cosmos metallic
RFID reader	Digta RFID 414, color Cosmos metallic
Rechargeable battery	Li-Polymer 950 mA, 3,7 V rechargeable battery

Please make sure to choose only genuine accessories from Grundig. Product liability and warranty service are provided only in this case. The use of non-Grundig accessories or those which are not recommended and approved by Grundig automatically void any warranty claims towards Grundig. Grundig Business Systems GmbH, Emmericher Str. 17, D-90411 Nuremberg, E-Mail: info@grundig-gbs.com, Internet: www.grundig-gbs.com.

In the US: GBS, 2135 City Gate Ln., Suite 300, Naperville, IL 60563, Phone: +1 312-924-2878  
Printed in Germany. We reserve the right to make technical changes and improvements. ORDER NUMBER: HNE 6156 08/2009